

Cambridge Audio

# Tech specs

## Azur 340A SE integrated amplifier



### Azur 340A SE specifications

#### Features

Exceptionally low-noise preamp stage with sophisticated input switching technology

Front panel MP3 in

Oversized lowflux toroidal transformer

Audio inputs 5 line level, 1 tape loop

Other connections 1 1/4" / 6.35mm headphone output, 3.5mm jack for iPod/MP3 player

By-passable bass and treble controls

Speaker A/B

Solid aluminium front panel

Full function azur remote

Available in silver/black

#### Performance

Power output 45 watts (into 8 ohms)  
55 watts (into 4 ohms)

Max power consumption 360 watts

Input impedance 40k Ohms

Loudspeaker impedance 4 – 8 Ohms

Input sensitivity Line: 350mV

Tone controls Bass: +/- 7dB @ 80Hz  
Treble: +/- 7dB @ 20Hz

Total harmonic distortion 1kHz < 0.09%  
1kHz < 0.09%

Frequency response (-1dB) 5Hz - 50kHz

Signal to noise ratio (unweighted) 92dB

Slew rate (into 8 ohms) 20V/uS

Dimensions (H x W x D) 70 x 430 x 310mm  
(2.8 x 16.9 x 12.2")

Weight 6.2kg (13.6Lbs)

Cambridge Audio's policy is one of continuous improvement. Design and specifications are therefore subject to change without prior notice.

Cambridge Audio, Gallery Court,  
Hankey Place, London, SE1 4BB, England  
© 2005 Cambridge Audio Ltd  
Issued: August 2006

 Cambridge Audio



**Azur 340A SE integrated amplifier**